



ICM401-50 & ICM401-60

PHASE LOSS and REVERSAL PROTECTION

- **Ultra low cost phase loss and phase reversal protection**

DESCRIPTION

- Low cost 3-phase protection for single side
- Monitors for phase reversal
- Monitors for phase loss
- Monitors for phase unbalance % as a function of input voltage
- Bright LED indicators for ON and FAULT
- Highly reliable passive electronics
- IEEE587 transient-tested
- Epoxy encapsulated for added protection
- **Patented:** US Patent No. 5,337,206

SPECIFICATIONS

Input

- **Voltage:** 190-600 VAC
- **Frequency:**
 - ICM401-50: 50 Hz
 - ICM401-60: 60 Hz
- **Control:** 18-30 VAC

Output

- **Ratings:**
 - **Type:** Relay
 - **Form:** SPST
 - **N.O.:** 10 amps

WIRING DIAGRAM

